



纯正正弦波转换充电一体机

当你在外面时需要电源吗？

带充电器的电源逆变器为车辆供电提供了一种新的能源供应形式。用户可以使用车载电源，通过设备转换电网电压，供负载使用。如果有电网，可以优先使用电网为负载供电，并同时为车载电池和备用电池充电，而无需再购买充电器。充电器为车辆供电提供了一种新的能源供应形式。用户可以使用车载电源，通过设备转换电网电压供负载使用。如果有电网，可以优先使用电网为负载供电，并同时为车载电池和备用电池充电，而不需要购买另一个充电器。



专业可靠DC端子设计



遥控配线

Pure Sine Wave Inverter & Charger

3000W

ETL RoHS



功能特点

- 快速充电，充电功率更高。
- 远程控制充电功率，为不同类型的电池提供最佳充电功率。
- 电池低电压保护，自动关机。
- 过温保护，自动关机。
- 输出短路保护。

PURE SINE WAVE & CHARGER



3000W

Functional mode	功能模式	Inverter	Charger
Rated power	额定功率	3000W	2400W
Rated input voltage	额定输入电压	12V DC	120V AC
Rated Output Voltage	额定输出电压	120V AC	14.4V DC
Output frequency	输出频率	60Hz	55-65Hz
Static power consumption	静态功耗	<12W	<12W
Input Voltage Range	输入电压范围	10.5VDC-15VDC	84VAC-144VAC
Output Voltage Range	输出电压范围	115VAC-125VAC	10VDC-14.4VDC
Overload protection power	过载保护功率	3300W	/
Peak power	峰值功率	6000W	/
Constant current charging	恒流充电	/	160A
Charging Voltage	充电电压	/	14.4VDC
Floating charging voltage	浮充电压	/	13.6VDC
Efficiency	最高转换效率	92%	/
Operation temperature	工作温度	-20°C to +50°C	
Storage temperature	储存温度	-25°C---+65°C	